

IN THE CLAIMS

The status of the claims is noted below.

1. (Currently Amended) Stereo demultiplexer receiving a frequency demodulated stereo-multiplex signal ($m(t)$) which comprises at least a stereo-difference signal ($m_d(t)$), a stereo-sum signal ($m_s(t)$) and a pilot carrier, comprising a PLL-circuit to recover the pilot carrier ~~and/or~~ or at least one harmonic thereof to perform an amplitude demodulation, wherein said PLL-circuit receives the sampling rate decimated stereo-sum signal ($m_s(t)$) as input signal, which is sampling rate decimated by a decimation factor of D.

2. (Previously Presented) Stereo demultiplexer according to claim 1, wherein said sampling rate decimated stereo-sum signal ($m_s(t)$) is further sampling rate decimated by a decimation factor of E before said PLL-circuit receives it as input signal.

3. (Currently Amended) Stereo demultiplexer receiving a frequency demodulated stereo-multiplex signal ($m(t)$) which comprises at least a stereo-difference signal ($m_d(t)$), a stereo-sum signal ($m_s(t)$) and a pilot carrier, comprising a PLL-circuit to recover the pilot carrier ~~and/or~~ or at least one harmonic thereof to perform an amplitude demodulation, wherein said PLL-circuit receives the sampling rate decimated stereo-sum signal ($m_s(t)$) as input signal, which is sampling rate decimated by a decimation factor of D,

wherein said PLL-circuit outputs a recovered pilot carrier which is interpolated so that it has a sampling rate equal to that of the frequency demodulated stereo-multiplex signal.

4 (Previously Presented) Stereo demultiplexer according to claim 3, wherein that D-1 or (E·D)-1 interpolated pilot carrier values ($y(k/D+1), \dots, y(k/D+(D-1))$) and one calculated pilot carrier value ($y(k/D)$) are alternately output.

5. (Previously Presented) Stereo demultiplexer according to claim 4, wherein said interpolation within the PLL-circuit is performed on basis of a prediction starting at said calculated pilot carrier value.

6. (Previously Presented) Stereo demultiplexer according to claim 5, including

- a PLL within the PLL-circuit which outputs a phase signal, and
- a first sine calculation unit which outputs said one calculated pilot carrier value ($y(k/D)$) on the basis of said phase signal.

7. (Previously Presented) Stereo demultiplexer according to claim 6, including

- second to D^{th} or $(E \cdot D)^{\text{th}}$ sine calculation units each of which outputs one of said $D-1$ or $(E \cdot D)-1$ interpolated pilot carrier values ($y(k/D+1)$, ..., $y(k/D+(D-1))$) on basis of said phase signal and a respective added phase shift value.

8. (Currently Amended) Stereo demultiplexer according to claim 6, including

- a third multiplexer which multiplies said phase signal with a factor of 2 before it is input to said first sine calculation unit ~~and/or~~ or a respective second to D^{th} or $(E \cdot D)^{\text{th}}$ sine calculation unit via a respective second to D^{th} or $(E \cdot D)^{\text{th}}$ adder which adds said respective phase shift value so that the 2^{nd} harmonic of the pilot carrier is generated.

9. (Previously Presented) Stereo demultiplexer according to claim 6, wherein said PLL comprises

- a first multiplier receiving samples of the stereo-sum signal ($x(k)$) as multiplicand at a first input,
- a filter receiving the output signal of said first multiplier,
- a second multiplier multiplying said output signal of said filter with a PLL gain (PLL_loop_gain),
- a first adder receiving said output signal of said second multiplier at a first input as a first summand, a constant representing the product of the pilot carrier frequency (ω_{pil}) and the sampling period at a second input as a second summand, and a delayed phase signal which is the output signal of said first adder at a third input as a third summand,
- a delay element receiving said phase signal of said first adder and supplying said delayed phase signal to said third input of said first adder, and
- a cosine calculation unit receiving the phase signal of said first adder and supplying its output signal as multiplier to a second input of said first multiplier.

10. (New) Stereo demultiplexer receiving a frequency demodulated stereo-multiplex signal ($m(t)$) which comprises at least a stereo-difference signal ($m_d(t)$), a stereo-sum signal ($m_s(t)$) and a pilot carrier, comprising a PLL-circuit to recover the pilot carrier and at least one harmonic thereof to perform an amplitude demodulation, wherein said PLL-circuit receives the sampling rate decimated stereo-sum signal ($m_s(t)$) as input signal, which is sampling rate decimated by a decimation factor of D .

11. (New) Stereo demultiplexer according to claim 10, wherein said sampling rate decimated stereo-sum signal ($m_s(t)$) is further sampling rate decimated by a decimation factor of E before said PLL-circuit receives it as input signal.

12. (New) Stereo demultiplexer receiving a frequency demodulated stereo-multiplex signal ($m(t)$) which comprises at least a stereo-difference signal ($m_d(t)$), a stereo-sum signal ($m_s(t)$) and a pilot carrier, comprising a PLL-circuit to recover the pilot carrier and at least one harmonic thereof to perform an amplitude demodulation, wherein said PLL-circuit receives the sampling rate decimated stereo-sum signal ($m_s(t)$) as input signal, which is sampling rate decimated by a decimation factor of D ,

wherein said PLL-circuit outputs a recovered pilot carrier which is interpolated so that it has a sampling rate equal to that of the frequency demodulated stereo-multiplex signal.

13. (New) Stereo demultiplexer according to claim 12, wherein that $D-1$ or $(E \cdot D)-1$ interpolated pilot carrier values ($y(k/D+1)$, ..., $y(k/D+(D-1))$) and one calculated pilot carrier value ($y(k/D)$) are alternately output.

14. (New) Stereo demultiplexer according to claim 13, wherein said interpolation within the PLL-circuit is performed on basis of a prediction starting at said calculated pilot carrier value.

15. (New) Stereo demultiplexer according to claim 14, including

- a PLL within the PLL-circuit which outputs a phase signal, and
- a first sine calculation unit which outputs said one calculated pilot carrier value ($y(k/D)$) on the basis of said phase signal.

16. (New) Stereo demultiplexer according to claim 15, including

- second to D^{th} or $(E \cdot D)^{\text{th}}$ sine calculation units each of which outputs one of said $D-1$ or $(E \cdot D)-1$ interpolated pilot carrier values ($y(k/D+1)$, ..., $y(k/D+(D-1))$) on basis of said phase signal and a respective added phase shift value.

17. (New) Stereo demultiplexer according to claim 15, including

- a third multiplexer which multiplies said phase signal with a factor of 2 before it is input to said first sine calculation unit and a respective second to D^{th} or $(E \cdot D)^{\text{th}}$ sine calculation unit via a respective second to D^{th} or $(E \cdot D)^{\text{th}}$ adder which adds said respective phase shift value so that the 2^{nd} harmonic of the pilot carrier is generated.

18. (New) Stereo demultiplexer according to claim 15, including

- a third multiplexer which multiplies said phase signal with a factor of 2 before it is input to said first sine calculation unit or a respective second to D^{th} or $(E \cdot D)^{\text{th}}$ sine calculation unit via a respective second to D^{th} or $(E \cdot D)^{\text{th}}$ adder which adds said respective phase shift value so that the 2^{nd} harmonic of the pilot carrier is generated.

19. (New) Stereo demultiplexer according to claim 15, wherein said PLL comprises

- a first multiplier receiving samples of the stereo-sum signal ($x(k)$) as multiplicand at a first input,
- a filter receiving the output signal of said first multiplier,
- a second multiplier multiplying said output signal of said filter with a PLL gain (PLL_loop_gain),
- a first adder receiving said output signal of said second multiplier at a first input as a first summand, a constant representing the product of the pilot carrier frequency (ω_{pil}) and the sampling period at a second input as a second summand, and a delayed phase signal which is the output signal of said first adder at a third input as a third summand,
- a delay element receiving said phase signal of said first adder and supplying said delayed phase signal to said third input of said first adder, and
- a cosine calculation unit receiving the phase signal of said first adder and supplying its output signal as multiplier to a second input of said first multiplier.

20. (New) Stereo demultiplexer according to claim 6, including

- a third multiplexer which multiplies said phase signal with a factor of 2 before it is input to said first sine calculation unit and a respective second to D^{th} or $(E \cdot D)^{\text{th}}$ sine calculation unit via a respective second to D^{th} or $(E \cdot D)^{\text{th}}$ adder which adds said respective phase shift value so that the 2^{nd} harmonic of the pilot carrier is generated.